


EW05

Self Excited Automatic Voltage Regulator

Compatible with 190/200/210 Type Welder / Generators Regulators

Features

- For use in 50/60 Hz brushless generators
- Single phase sensing, same as original
- External welding current adjustment
- External AC voltage adjustment
- Provides regulation for welder & AC output
- Automatic welder current compensation
- Compatible with original modules




EW05
www.kutai.com.tw

Specifications

Power Input	Voltage 90 to 130 Vac 1 phase 2 wire	Thermal Drift	0.05% per °C change in AVR ambient
Output	Voltage 45 Vdc @ 110 Vac	Current Compensation	Automatic welder current compensation
	Current Continuous 5A Intermittent 15A for 10 seconds	Current Adjustment	Welding current 50 to 190A
Build Up Voltage	Residual voltage at AVR terminal > 2 Vac		

Dimensions



Compatible Replacement for

BRAND	MODEL
SUZUKI	CCW-210, CCW-190H
HONDA	EW-190S
DAISHIN	SGW-200HX
KAIYU	SGW-190X

Environment

Operating Temperature	-40 to +60 °C
Storage Temperature	-40 to +85 °C
Relative Humidity	Max. 90%
Vibration	1.5 Gs @ 5 to 30 Hz 5.0 Gs @ 30 to 500 Hz

Physical Specifications

Dimensions	100.0 (L) x 72.0 (W) x 46.7 (H) mm
Weight	224 g +/-2%

*All manufacturer names and numbers are used for reference purpose only and do not imply that any part is the product of these manufacturer.



KUTAI ELECTRONICS INDUSTRY CO., LTD.
TEL : +886-7-8121771 FAX : +886-7-8121775 Website : www.kutai.com.tw
Headquarters : No.3, Ln. 201, Qianfu St., Qianzhen Dist., Kaohsiung City 80664, Taiwan

